

Product Specification Sheet

Model: MS3710-02

MS3700

Slim Plug-In Potentiometer Transmitter with Isolated Single/Dual Output (Constant Current Model)

DESCRIPTION

The MS3710-02 is a slim, plug-in constant-current potentiometer transmitter that detects changes in the resistance of potentiometric sensors, converts them into commonly used DC signals and provides isolated single or dual output.

ORDERING CODE

MS3710-02 - 🗆 - 🔲 🔲 Model Power Supply -**A**: 100 to 240V AC (50 to 60Hz) **D**: 24V DC **P**: 100 to 240V DC Input Range between $0\text{-}100\Omega$ and $0\text{-}10k\Omega$ Output 1 -**A**: 4 to 20mA DC 1: 0 to 10mV DC **D**: 0 to 20mA DC 2: 0 to 100mV DC **Z**: Other DC current signal 3: 0 to 1V DC 4: 0 to 10V DC **5**: 0 to 5V DC **6**: 1 to 5V DC **3W**: ±1V DC 4W: ±10V DC **5W**: ±5V DC

Output 2 -

No code: None

The codes are the same as for Output 1.

Note 1: When a voltage output is selected for Output 1, a current output cannot be selected for Output 2.

0: Other DC voltage signal

- Note 2: When the code A (4 to 20mA) is selected for both of the two outputs, the output load will be 550Ω maximum for Output 1 and 350Ω maximum for Output 2.
- Note 3: Burnout protection is upscale.

Options

No code: None


/K: Fast response (0 to 90% response time: 10ms max.)

/L: Dual current output with high output load

 $(OUT-1: 750\Omega / OUT-2: 550\Omega)$

/X: Others (Special order)

* For non-standard options, ask MTT for availability.





ORDERING INFORMATION

To place an order, please use the ordering code format as shown on the left.

(e.g.) MS3710-02-A-A6 (0 to 100Ω)

Other Ordering Examples:

For an output code of "0": MS3710-02-A-06 (0 to 100Ω /

Output: 2 to 5V)

For an option code of "X": MS3710-02-A-A/X (0 to $10k\Omega$ /

Response frequency: 50Hz)

Note: If you wish to include multiple options in your order, specify the option codes in series (e.g. /KX).

SPECIFICATIONS

POWER SECTION

	Power	100 to 24	UV AC: 85 to	204 V AC (47
	Requirements	to 63Hz)		
	•	24V DC:	24V DC±10%	ó
		100 to 24	0V DC: 85 to	264V DC
_	Power Sensitivi	ty Better tha	ın ±0.1% of sp	oan for each
_		power su	oply range.	
_	Power Line Fus	e 160mA fu	ise is installed	l (standard).
_	Power Consumption			
	Power	100-240V AC	24V DC	100-240V DC
	Single Output	5.5VA max	1.6W max	6.0W max
	Dual Output	7.0VA max	1.8W max	6.0W max
_				

INPUT SECTION

Excitation	Approx. 1mA: Input range between
Current	$0-100\Omega$ and $0-2k\Omega$.
	Approx. 0.2mA: Input range between
	$0\text{-}2k\Omega$ and $0\text{-}10k\Omega$.
Allowable Lead	200Ω max. per wire
Wire Resistance	
Ranges Available	

<Standard specifications>

Specify between $0-100\Omega$ and $0-1k\Omega$ in steps of 10Ω . Specify between $0-1k\Omega$ and $0-10k\Omega$ in steps of 100Ω .

Note: Any specification out of the above listed requirement is handled as a special order.

Maximum Output Load Voltage Output 1V span and up (DC) 10mV 100mV

 $\begin{array}{lll} 10 mV & 10 k\Omega \text{ min.} \\ 100 mV & 100 k\Omega \text{ min.} \\ 4-20 mA \text{ single output} & 750 \Omega \text{ max.} \\ 4-20 mA \text{ dual output} & 0 \text{utput 1:} \\ & 550 \Omega \text{ max.} \end{array}$

Output 2: 350Ω max.

2mA max.

Zero Adjustment Approx. $\pm 5\%$ of span. (Adjustable by the front-accessible trimmer.)

Span Adjustment Approx. ±5% of span.
(Adjustable by the front-accessible trimmer.)

Ranges Available

Current Output

(DC)

 $\begin{array}{c} \text{Current Signal} & \text{Voltage Signal} \\ \text{Output Range (DC)} & 0 \text{ to } 20\text{mA} & -10 \text{ to } 10\text{V} \\ \text{Output Span (DC)} & 4 \text{ to } 20\text{mA} & 10\text{mV to } 20\text{V} \\ \text{Output Bias} & 0 \text{ to } 100\% & -100 \text{ to } 100\% \end{array}$

* For current output signals, the accuracy of any current output smaller than 0.1mA is not guaranteed.

Output Spec. Ex.1: For 4 to 20mA output, the output span is 16mA and the bias +25%.

Output Spec. Ex. 2: For -1 to 4V output, the output span is 5V and the bias -20%.

PERFORMANCE


PERFORMANCE				
Accuracy Rating	Better than ±0.2% of span (at			
, ,	25°C±5°C).			
Temperature	Better than ±0.2% of span per 10°C			
Effect	change in ambient.			
Response Time	170ms max. (0 to 90%) with a step			
	input at 100%.			
CMRR	100dB min. (500V AC, 50/60Hz)			
Isolation	4-way isolation between input, output			
	[Output 1/Output 2], power, and			
	ground.			
Insulation	$100M\Omega$ min. (@ 500V DC) between			
Resistance	input, output [Output 1/Output 2],			
	power, and ground.			
Dielectric	Input / Output [Output 1/Output 2] /			
Strength	[Power, Ground]: 2000V AC for 1			
	minute (Cutoff current: 0.5mA)			
	Power / Ground: 2000V AC for 1			
	minute (Cutoff current: 5mA)			
	Output 1 / Output 2: 500V AC for 1			
	minute (Cutoff current: 0.5mA)			
Surge Withstand	Tested as per ANSI/IEEE			
Capability	C37.90.1-1989.			
Operating	Ambient temperature: -5 to 55°C			
Environment	Humidity: 5 to 90% RH			
	(non-condensing)			
Storage	-10 to 60°C			
Temperature				

PHYSICAL

01111010712		
Installation	Wall/DIN rail mounting	
Wiring	M3.5 screw terminal connection	
	(with a power terminal block cover &	
	drop-out prevention screws)	
Screwing Torque	0.8 to 1.0 [Nm] * Recommended	
External	$W29 \times H86 \times D125$ mm	
Dimensions	(including the mounting screw and	
	socket)	
Weight	Main unit: 120g max.	
	Socket: 80g max.	
• MATERIALS		
Housing	ABS resin (UL 94V-0)	
Terminal Block	PBT resin (UL 94V-0)	
Terminal Block	PC resin (UL 94V-2)	
Cover		
DIN Rail Stopper	PP resin (UL 94HB)	
Screw Terminal	Nickel-plated steel	
Contacts Material	Brass with 0.2µm gold plating	
and Finish		
Printed Circuit	Glass fabric epoxy resin	
Board	(FR-4: UL 94V-0)	
Anti-Humidity	HumiSeal® 1A27NS (Polyurethane)	
Coating	======= (a (1 or) arounding)	

^{*} HumiSeal® is a registered trademark of Chase Corporation.

TERMINAL ASSIGNMENT



1	P (+)	POWER	
2	N (-)	POWER	
Ŧ	GND		
4	+ OUTPUT 1		
(5)	- OUTPUT 1		
6	N.C.		
\bigcirc	+ OUTPUT 2		
8	- OUTPUT 2		
9	A POT		
10	В РОТ		
11	B' POT	•	

BLOCK DIAGRAM

